


PowerBook G3 Lombard Processor Replacement

Written By: iRobot



INTRODUCTION

This processor board also includes L2 cache. It is not soldered to the logic board, so installing a replacement is very easy.

TOOLS:

- Anti-Static Wrist Strap (1)
- Phillips #0 Screwdriver (1)
- Spudger (1)

PARTS:


- G3 Lombard 333 MHz Processor (1)
- G3 Lombard 400 MHz Processor (1)

Step 1 — Keyboard



- Turn the computer so that the ports are facing you.
- If the keyboard is locked, open the port cover and turn the keyboard locking screw until the keyboard is unlocked.

Step 2




- Pull the keyboard release tabs toward you and lift up on the keyboard until it pops free.
- (i) Make sure you have removed the laptop battery and CD/DVD module from the expansion bays before proceeding.




- Lift the keyboard out by pulling it up and away from you. Rest the keyboard, face down, on top of the trackpad.
- (i) In order to replace the keyboard, you must first remove the modem.

Step 4 — Heat Shield



• Remove the three silver Phillips screws that attach the heat shield to the internal metal framework.



• Lift the heat shield up and pull it toward you.

Step 6



• Your laptop should look approximately like this.

Step 7 — PRAM Battery



• Pull the battery cable directly up from the logic board.

Step 8



• Remove the battery from its holder by pulling up and to the left.

Step 9 — Modem



• Remove the two silver Phillips screws from the modem.



• Use a spudger, the tips of your fingers, or a flat non-metal tool to get under the modem's edge and pry it up from its socket as shown in the picture.

Step 11



• Disconnect the cable from the right side of the modem.



• Your laptop should look approximately like this.

Step 13 — Processor



• Use a spudger, the tips of your fingers, or a flat non-metal tool to pry up the processor's right side.



- Disconnect the keyboard cable from the logic board by pulling directly up on the clear plastic loop.
- (i) This step is out of sequence with the keyboard because in order to remove the keyboard you must first remove the modem.

Step 15



• Your laptop should look approximately like this.

To reassemble your device, follow these instructions in reverse order.